ROOSEVELT — PROJECT NO. 270.032

VOLTS 120/208
PHASE 3PH, 4W
MTG SURFACE

PANELBOARD PK1 — MAIN L.G.
LOCATION CUSTODIAN #5 — BUS 200A/3P

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
1	2736	-----	-----	K	40/3	1	REFRIGERATION SYSTEM
3	-----	2736	-----	K	--	-	----------
5	-----	-----	2736	K	--	-	----------
7	1130	-----	-----	K	20/1	1	INSECT CONTROL FAN
9	-----	1000	-----	K	20/1	1	X1-EXHAUST HOOD
11	-----	-----	720	K	20/1	1	X1-CONVECTION OVEN
13	720	-----	-----	K	20/1	1	X1-CONVECTION OVEN
15	-----	500	-----	K	20/1	1	D.W. EXHAUST HOOD
17	-----	-----	510	M	20/1	1	EF-21
19	900	-----	-----	K	20/3	1	DISPOSER
21	-----	900	-----	K	--	-	----------
23	-----	-----	900	K	--	-	----------
25	1498	-----	-----	K	20/2	1	HOT FOOD COUNTER
27	-----	1498	-----	K	--	-	----------
29	-----	-----	100	G	20/1	2	*SMOKE/FIRE DAMPER
31	360	-----	-----	R	20/1	2	SHADE RECEPTACLES
33	-----	-----	-----				PROVISION
35	-----	-----					PROVISION
37		-----	-----				PROVISION
39	-----		-----				PROVISION
41	-----	-----					PROVISION

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
A 2	276	-----	-----	K	20/1	1	WALK IN COOLER
B 4	-----	276	-----	K	20/1	1	WALK IN COOLER
C 6	-----	-----	1196	K	20/2	1	EVAPORATOR COIL
A 8	1196	-----	-----	K	--	-	----------
B 10	-----	516	-----	K	20/1	1	EVAPORATOR COIL
C 12	-----	-----	2000	K	20/1	1	HEATED CABINET
A 14	3216	-----	-----	K	40/3	1	DISHWASHER
B 16	-----	3216	-----	K	--	-	----------
C 18	-----	-----	3216	K	--	-	----------
A 20	6498	-----	-----	K	60/3	1	BOOSTER HEATER
B 22	-----	6498	-----	K	--	-	----------
C 24	-----	-----	6498	K	--	-	----------
A 26	70	-----	-----	M	15/2	1	FC-8
B 28	-----	70	-----	M	--	-	----------
C 30	-----	-----	70	M	15/2	1	FC-7
A 32	70	-----	-----	M	--	-	----------
B 34	-----	100	-----	G	20/1	1	* GAS SOLENOID
C 36	-----	-----	200	G	20/1	1	* FSR BELL
A 38		-----	-----		20/1		SPARE
B 40	-----	-----	-----		20/1		SPARE
C 42	-----	-----			20/1		SPARE

CONNECTED:	VA	AMPS
PHASE A =	18670	156
PHASE B =	17310	144
PHASE C =	18146	151
TOTAL =	54126	150

L.C.L. @ 125% =	0
RECEPT. ( ) 10 VAA @ 500) =	360
KITCHEN @ 65% =	34174
OTHER LOAD @ 100% =	1190
TOTAL VA =	35724
TOTAL AMPS =	99

LOAD TYPE:
G - GENERAL (100%) M - MOTOR (100%)
L - L.C.L. (125%) M1 - MOTOR (125%)
R - RECEPTACLE (50%) X - X-RAY (100%)
(10 VAA @ 100%) X1 - X-RAY (50%)
K - KITCHEN (65%)

* PROVIDE LOCK-ON DEVICE ON CIRCUIT BREAKER. LABEL "FIRE ALARM".

X1 - PROVIDE MULTI-POLE CONTACTOR TO CONTROL EQUIPMENT UNDER KITCHEN HOOD. CONNECT TO FIRE SUPPRESION SYSTEM.

ROOSEVELT — PROJECT NO. 270.032

VOLTS 277/480
PHASE 3PH, 4W
MTG SURFACE

PANELBOARD DPHK — MAIN 400A/3P
LOCATION ELECT. ROOM #4 — BUS 400A

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
1	28470	-----	-----	G	200/3	1	TRANSFORMER KOHR
3	-----	26326	-----	G	--	-	----------
5	-----	-----	27772	G	--	-	----------
7	1975	-----	-----	L	100/3	1	PANELBOARD HK1
9	-----	2916	-----	L	--	-	----------
11	-----	-----	460	L	--	-	----------
13	-----	-----	-----				PROVISION
15	-----	-----	-----				PROVISION
17	-----	-----					PROVISION
19		-----	-----				PROVISION
21	-----	-----					PROVISION
23	-----	-----					PROVISION
25		-----	-----				PROVISION
27	-----	-----					PROVISION
29	-----	-----					PROVISION
31	-----	-----					PROVISION
33	-----	-----					PROVISION
35	-----	-----					PROVISION
37	-----	-----					PROVISION
39	-----	-----					PROVISION
41	-----	-----					PROVISION

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
A 2	18798	-----	-----	L	225/3	1	PANELBOARD HC1
B 4	-----	16356	-----	L	--	-	----------
C 6	-----	-----	15380	L	--	-	----------
A 8	2936	-----	-----	M1	20/3	1	AC-40
B 10	-----	2936	-----	M1	--	-	----------
C 12	-----	-----	2936	M1	--	-	----------
A 14	1915	-----	-----	M1	20/3	1	MUA-1
B 16	-----	1915	-----	M1	--	-	----------
C 18	-----	-----	1915	M1	--	-	----------
A 20		-----	-----				PROVISION
B 22	-----	-----	-----				PROVISION
C 24	-----	-----					PROVISION
A 26		-----	-----				PROVISION
B 28	-----	-----					PROVISION
C 30	-----	-----					PROVISION
A 32		-----	-----				PROVISION
B 34	-----	-----					PROVISION
C 36	-----	-----					PROVISION
A 38		-----	-----				PROVISION
B 40	-----	-----					PROVISION
C 42	-----	-----					PROVISION

CONNECTED:	VA	AMPS
PHASE A =	54094	195
PHASE B =	50649	183
PHASE C =	49463	175
TOTAL =1	53206	184

L.C.L. @ 125% =	88298
RECEPT. ( ) 10 VAA @ 500) =	0
KITCHEN @ 65% =	0
OTHER LOAD @ 100% =	82568
TOTAL VA =	170866
TOTAL AMPS =	206

LOAD TYPE:
G - GENERAL (100%) M - MOTOR (100%)
L - L.C.L. (125%) M1 - MOTOR (125%)
R - RECEPTACLE (50%) X - X-RAY (100%)
(10 VAA @ 100%) X1 - X-RAY (50%)
K - KITCHEN (65%)

ROOSEVELT — PROJECT NO. 270.032

VOLTS 120/208
PHASE 3PH, 4W
MTG SURFACE

PANELBOARD PK2 — MAIN L.G.
LOCATION CUSTODIAN #5 — BUS 125A/3P

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
1	884	-----	-----	M1	20/2	1	CU-8
3	-----	884	-----	M1	--	-	----------
5	-----	-----	720	R	20/1	4	ROOF RECEPTS.
7	888	-----	-----	M1	20/2	1	CU-7
9	-----	884	-----	M1	--	-	----------
11	-----	-----	500	G	20/1	1	CP-1
13	670	-----	-----	M	20/1	1	EF-23
15	-----	-----	-----		20/1		SPARE
17	-----	-----	670	M	20/1	1	EF-22
19		-----	-----				PROVISION
21	-----	-----					PROVISION
23	-----	-----					PROVISION
25		-----	-----				PROVISION
27	-----	-----					PROVISION
29	-----	-----					PROVISION
31		-----	-----				PROVISION
33	-----	-----					PROVISION
35	-----	-----					PROVISION
37		-----	-----				PROVISION
39	-----	-----					PROVISION
41	-----	-----					PROVISION

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
A 2	1000	-----	-----	G	20/1	2	COMPUTER RECEPTS.
B 4	-----	720	-----	R	20/1	4	CONV. RECEPTS.
C 6	-----	-----	720	R	20/1	4	CONV. RECEPTS.
A 8	552	-----	-----	K	20/1	1	MILK COOLER
B 10	-----	1080	-----	R	20/1	6	CONV. RECEPTS.
C 12	-----	-----	500	G	20/1	1	IBFK
A 14	500	-----	-----	G	20/1	1	EMSK
B 16	-----	500	-----	G	20/1	1	IBK
C 18	-----	-----	500	G	20/1	1	FSPK
A 20		-----	-----				PROVISION
B 22	-----	-----					PROVISION
C 24	-----	-----					PROVISION
A 26		-----	-----				PROVISION
B 28	-----	-----					PROVISION
C 30	-----	-----					PROVISION
A 32		-----	-----				PROVISION
B 34	-----	-----					PROVISION
C 36	-----	-----					PROVISION
A 38		-----	-----				PROVISION
B 40	-----	-----					PROVISION
C 42	-----	-----					PROVISION

CONNECTED:	VA	AMPS
PHASE A =	4494	37
PHASE B =	4368	34
PHASE C =	3610	30
TOTAL =	12172	34

L.C.L. @ 125% =	4425
RECEPT. ( ) 10 VAA @ 500) =	3240
KITCHEN @ 65% =	359
OTHER LOAD @ 100% =	4940
TOTAL VA =	12864
TOTAL AMPS =	36

LOAD TYPE:
G - GENERAL (100%) M - MOTOR (100%)
L - L.C.L. (125%) M1 - MOTOR (125%)
R - RECEPTACLE (50%) X - X-RAY (100%)
(10 VAA @ 100%) X1 - X-RAY (50%)
K - KITCHEN (65%)

ROOSEVELT — PROJECT NO. 270.032

VOLTS 120/208
PHASE 3PH, 4W
MTG SURFACE

PANELBOARD DPPK — MAIN 600A/3P
LOCATION ELECT. ROOM #4 — BUS 600A

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
1	5666	-----	-----	G	225/3	1	PANELBOARD PC1
3	-----	4948	-----	G	--	-	----------
5	-----	-----	6214	G	--	-	----------
7	-----	-----	-----				PROVISION
9	-----	-----					PROVISION
11	-----	-----					PROVISION
13	-----	-----	-----				PROVISION
15	-----	-----					PROVISION
17	-----	-----					PROVISION
19	-----	-----	-----				PROVISION
21	-----	-----					PROVISION
23	-----	-----					PROVISION
25	-----	-----	-----				PROVISION
27	-----	-----					PROVISION
29	-----	-----					PROVISION
31	-----	-----	-----				PROVISION
33	-----	-----					PROVISION
35	-----	-----					PROVISION
37	-----	-----	-----				PROVISION
39	-----	-----					PROVISION
41	-----	-----					PROVISION

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
A 2	18310	-----	-----	G	200/3	1	PANELBOARD PK1
B 4	-----	17310	-----	G	--	-	----------
C 6	-----	-----	17946	G	--	-	----------
A 8	4494	-----	-----	G	125/3	1	PANELBOARD PK2
B 10	-----	4068	-----	G	--	-	----------
C 12	-----	-----	3610	G	--	-	----------
A 14	-----	-----	-----				PROVISION
B 16	-----	-----					PROVISION
C 18	-----	-----					PROVISION
A 20	-----	-----	-----				PROVISION
B 22	-----	-----					PROVISION
C 24	-----	-----					PROVISION
A 26	-----	-----	-----				PROVISION
B 28	-----	-----					PROVISION
C 30	-----	-----					PROVISION
A 32	-----	-----	-----				PROVISION
B 34	-----	-----					PROVISION
C 36	-----	-----					PROVISION
A 38	-----	-----	-----				PROVISION
B 40	-----	-----					PROVISION
C 42	-----	-----					PROVISION

CONNECTED:	VA	AMPS
PHASE A =	28470	237
PHASE B =	26326	219
PHASE C =	27770	231
TOTAL =	82566	229

L.C.L. @ 125% =	
RECEPT. ( ) 10 VAA @ 500) =	
KITCHEN @ 65% =	
OTHER LOAD @ 100% =	82566
TOTAL VA =	82566
TOTAL AMPS =	229

LOAD TYPE:
G - GENERAL (100%) M - MOTOR (100%)
L - L.C.L. (125%) M1 - MOTOR (125%)
R - RECEPTACLE (50%) X - X-RAY (100%)
(10 VAA @ 100%) X1 - X-RAY (50%)
K - KITCHEN (65%)

ROOSEVELT — PROJECT NO. 270.032

VOLTS 277/480
PHASE 3PH, 4W
MTG SURFACE

PANELBOARD EHK — MAIN
LOCATION CUSTODIAN #5 — BUS 100A/3P

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
1	105	-----	-----	L	20/1	7	*BUILDING G EXIT SIGNS
3	-----	165	-----	L	20/1	11	*BUILDING C EMERG. EGRESS LTG.
5	-----	-----	90	L	20/1	2	X1-BUILDING C EXT. EGRESS LTG.
7	75	-----	-----	L	20/1	5	*BUILDING K EXIT SIGNS
9	-----	140	-----	L	20/1	4	*BUILDING K EMERG. EGRESS LTG.
11	-----	-----	225	L	20/1	5	X1-BUILDING K EXT. EGRESS LTG.
13		-----	-----		20/1		SPARE
15	-----	-----			20/1		SPARE
17	-----	-----			20/1		SPARE
19		-----	-----				PROVISION
21	-----	-----					PROVISION
23	-----	-----					PROVISION
25		-----	-----				PROVISION
27	-----	-----					PROVISION
29	-----	-----					PROVISION
31		-----	-----				PROVISION
33	-----	-----					PROVISION
35	-----	-----					PROVISION
37		-----	-----				PROVISION
39	-----	-----					PROVISION
41	-----	-----					PROVISION

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
A 2	90	-----	-----	L	20/1	6	*BUILDING G EXIT SIGNS
B 4	-----	210	-----	L	20/1	6	*BUILDING G EMERG. EGRESS LTG.
C 6	-----	-----	225	L	20/1	2	X1-BUILDING G EXT. EGRESS LTG.
A 8	270	-----	-----	L	20/1	6	LIGHTING
B 10	-----	360	-----	R	20/1	2	RECEPTACLES
C 12	-----	-----	500	G	20/1	1	BATTERY CHARGER
A 14	500	-----	-----	G	20/1	1	JACKET HEATER
B 16	-----				20/1		SPARE
C 18	-----	-----			20/1		SPARE
A 20		-----	-----				PROVISION
B 22	-----	-----					PROVISION
C 24	-----	-----					PROVISION
A 26		-----	-----				PROVISION
B 28	-----	-----					PROVISION
C 30	-----	-----					PROVISION
A 32		-----	-----				PROVISION
B 34	-----	-----					PROVISION
C 36	-----	-----					PROVISION
A 38		-----	-----				PROVISION
B 40	-----	-----					PROVISION
C 42	-----	-----					PROVISION

CONNECTED:	VA	AMPS
PHASE A =	1040	4
PHASE B =	875	3
PHASE C =	1040	4
TOTAL =	2955	4

L.C.L. @ 125% =	1994
RECEPT. ( ) 10 VAA @ 500) =	360
KITCHEN @ 65% =	0
OTHER LOAD @ 100% =	1000
TOTAL VA =	3354
TOTAL AMPS =	4

LOAD TYPE:
G - GENERAL (100%) M - MOTOR (100%)
L - L.C.L. (125%) M1 - MOTOR (125%)
R - RECEPTACLE (50%) X - X-RAY (100%)
(10 VAA @ 100%) X1 - X-RAY (50%)
K - KITCHEN (65%)

X1 - INDICATES CIRCUIT CONTROLLED BY MULTI-POLE RELAY OPERATED BY PHOTOCELL ON/PHOTOCELL OFF FUNCTION OF EXTERIOR LIGHTING CONTROLLER.
MOUNT RELAY IN A SEPARATE BARRIERED COMPARTMENT.

* PROVIDE CIRCUIT BREAKER LOCK-ON DEVICE.

ROOSEVELT — PROJECT NO. 270.032

VOLTS 277/480
PHASE 3PH, 4W
MTG SURFACE

PANELBOARD HK1 — MAIN L.G.
LOCATION BUILDING K ROOM 4 — BUS 100A

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
1	595	-----	-----	L	20/1	11	SERVING LINE LTG.
3	-----	1216	-----	L	20/1	18	KITCHEN LTG.
5	-----	-----	600	L	20/1	12X2-	SHADE STRUCT. LIGHTS
7		-----	-----		20/1		SPARE
9	-----	-----			20/1		SPARE
11	-----	-----			20/1		SPARE
13		-----	-----		20/1		SPARE
15	-----	-----			20/1		SPARE
17	-----	-----			20/1		SPARE
19		-----	-----				PROVISION
21	-----	-----					PROVISION
23	-----	-----					PROVISION
25		-----	-----				PROVISION
27	-----	-----					PROVISION
29	-----	-----					PROVISION

CKT	LOAD (VA) A	B	C	TYPE	BKR	OUTLET QUAN	DESCRIPTION
A 2	920	-----	-----	L	20/2	2	X1-PARKING LOT LTG.
B 4	-----	920	-----	L	--	-	X1--------
C 6	-----	-----	460	L	20/2	2	X2-PARKING LOT LTG.
A 8	460	-----	-----	L	--	-	X2--------
B 10	-----	780	-----	L	20/1	6	X1-WALKWAY LTS.
C 12	-----	-----	300	L	20/1	6	X2-COVERED WALKWAY LTG.
A 14		-----	-----		20/1		SPARE
B 16	-----	-----			20/1		SPARE
C 18	-----	-----			20/1		SPARE
A 20		-----	-----				PROVISION
B 22	-----	-----					PROVISION
C 24	-----	-----					PROVISION
A 26		-----	-----				PROVISION
B 28	-----	-----					PROVISION
C 30	-----	-----					PROVISION

CONNECTED:	VA	AMPS
PHASE A =	1975	7
PHASE B =	2916	11
PHASE C =	1360	5
TOTAL =	6251	8

L.C.L. @ 125% =	7814
RECEPT. ( ) 10 VAA @ 500) =	
KITCHEN @ 65% =	
OTHER LOAD @ 100% =	
TOTAL VA =	7814
TOTAL AMPS =	9

LOAD TYPE:
G - GENERAL (100%) M - MOTOR (100%)
L - L.C.L. (125%) M1 - MOTOR (125%)
R - RECEPTACLE (50%) X - X-RAY (100%)
(10 VAA @ 100%) X1 - X-RAY (50%)
K - KITCHEN (65%)

X1 ? INDICATES CIRCUIT CONTROLLED BY MULTI-POLE RELAY OPERATED BY PHOTOCELL ON / PHOTOCELL OFF FUNCTION OF THE ENERGY MANAGEMENT SYSTEM.
MOUNT RELAYS IN LIGHTING TERMINAL CABINET LOC.

X2 ? INDICATES CIRCUIT CONTROLLED BY MULTI-POLE RELAY OPERATED BY PHOTOCELL ON / TIMECLOCK OFF FUNCTION OF THE ENERGY MANAGEMENT SYSTEM.
MOUNT RELAYS IN LIGHTING TERMINAL CABINET LOC.

PK1	DPHK
PK2	DPPK
EHK	HK1

LICENSED ARCHITECT — JAMES M. STUDDER — C19098 — RENEWAL 08/28/ — STATE OF CALIFORNIA

REGISTERED PROFESSIONAL ENGINEER — STEPHEN R. ZAK — No. E 10272 — Exp. 06-30-12 — ELECTRICAL — STATE OF CALIFORNIA

FBA Engineering — Consulting Electrical Engineers — 3420 Tyler, Riverside, CA 92501 — Tel: 951 686 1960 FAX: 951 686 1987 — EMAIL: info@fbaengineering.net — FBA # 270.032

REVISIONS	DATE
1	- - - - - -
2	- - - - - -
3	- - - - - -
4	- - - - - -
5	- - - - - -
6	- - - - - -

P S W C GROUP
ARCHITECTS / PLANNERS
1867 BUSINESS CENTER DR., SUITE 3, SAN BERNARDINO, CA. 92408
909/890-2244 FAX. 909/890-2233

ROOSEVELT II
ELEMENTARY SCHOOL
SAN BERNARDINO CITY UNIFIED SCHOOL DISTRICT
1261 W. 16TH STREET, SAN BERNARDINO, CA.

KITCHEN
PANEL SCHEDULES

JOB NO. P0620
DRAWN BY FBA
DATE 12/9/2011

E-K.4

RE-BID #F09-02 ROOSEVELT II (HENRY) E.S. NEW CONSTRUCTION BID ISSUANCE SET 12/09/11

Filename: J:\PROJECTS\P0620\Elec\Panelsch
Plotted on Mon Dec 12, 2011 Time: 1:09 PM
Layout: TITLEBLOCK